

Cisco 9841/9851 Phone (effective 2026 – 2027)



Phone Features (soft keys/buttons)


- | | |
|---|--|
| 1. Phone Screen | 8. Speakerphone, Headset, Mute Buttons |
| 2. Status LED | 9. Keypad |
| 3. EMERGENCY ONLY - Public Safety – calls 2111 | 10. Volume |
| 4. Line/Feature Keys | 11. Voicemail, Settings, Directory (see closeup image below) |
| 5. Soft keys | 12. Status LED arc |
| 6. NFC Tag | 13. Menu Navigation |
| 7. Hold, Transfer, Conference Buttons (see closeup image below) | |

Please note: The display screen is not a touch screen. The functionality of the soft keys will change depending on the feature you are using.

Line Button Status Lights (4 on Diagram)

- | | |
|-------------------------------------|--------------------------------------|
| • Green Steady - Active / Two Way | • Green Flashing - Held Call |
| • Amber Steady - Privacy / Intercom | • Amber Flashing - Incoming Call |
| • Red Steady - Remote Line in Use | • Red Flashing - Remote Call on Hold |

Call Handling



External Calls

- Domestic: 1 + Area Code + Number
- Emergency External: 911
- Service Codes: 311, 711

Placing a Call

- Pick up the handset and dial the number.
- Pre-dial the number and then press “**Call**”.
- Begin pre-dialing the number and use the navigation ring to make a selection.
- Press “**Settings**” and then “**Recents**” to browse call history. You may need to insert a 1 prefix with the “**edit dial**” function.

Answering a Call

- Lift handset or press the “**Answer**” soft key.
- Press the Speaker (8 on Diagram).

Internal Calls

- Dial 4 Digit Extension

Placing a Call on Hold

- Press the “**Hold**” soft key.

Resuming a Call on Hold

- Select Line Key Corresponding to Call (4 on Diagram).
- Press the “**Resume**” soft key.

Call Transfer

While on an Active Call:

1. Press the Transfer Button/soft key (7 on Diagram).
2. Dial the intended party.
3. Press the Transfer Button again.

Note: If the party does not wish to take the call:

- Press the “**Cancel**” soft key.
- Press the “**Resume**” soft key.

Conference Calls

Ad Hoc Conference (Max 6 Participants)

While on an Active Call:

1. Press the Conference Button (7 on Diagram).
2. Dial the intended party.
3. Press the **Conference Button** again when the call is answered.
4. Repeat to add additional participants.

Note: If the party does not wish to take the call:

1. Before pressing the Conference Button again, => Press the “**End Call**” soft key.
2. Press the “**Resume**” soft key.

Removing Conference Participants

1. If necessary, scroll to page 2 of the screen using the “...” soft key.
2. Press the “**Show Detail**” soft key.
3. Highlight the party you wish to remove using the menu navigation selector (13 on Diagram).
4. Press the “**remove**” soft key.

Call Forwarding

Forward to another extension:

1. Press the “**Forward all**” soft key.
2. Dial the 4-digit extension.

Forward to voicemail:

1. Press the “**Forward all**” soft key.
2. Dial 5000 or press the Favorites button and select “**Voicemail.**”

Forward to a mobile or external number:

1. Press the “**Forward all**” soft key.
2. Dial 1+Area Code+Number.
3. You will get confirmation, and the display will show that the call is forwarded.

Cancel call forwarding:

1. Press the “**Forward off**” soft key.

Contacts / Directory



Viewing Call Logs

- Press Settings and select “**Recents**” to View Missed, dialed, and Received Calls:
 - Missed calls are highlighted in red.
 - Use the menu navigation ring to move between All, Placed, Received, and Missed tabs.

Using the CUNY Directory

To access the CUNY Directory:

1. Press the Contacts / Directory Button (11 on Diagram).
2. Select Custom Directory using the menu navigation selector (13 on Diagram).
3. Select CUNY Directory.
4. Enter a few characters of the First Name, Last Name, or Number and press “**Search**”.
5. Press “**Call**” when you see the name you want to call.

Do Not Disturb (DND)

1. If necessary, scroll to page 2 by pressing the “...” soft key.
2. Press the “**DND**” soft key to toggle **Do Not Disturb** mode.
 1. The screen will have a red line across the top to indicate that DND mode is currently active.